
SWP2061 Operation Manual

S-Video 1x6 Passive Video Switches

MicroImage Video Systems
division of World Video Sales Co., Inc.

P.O. Box 331
Boyertown, PA 19512
610-754-6800
Fax 610-754-9766
info@mivs.com

www.mivs.com

Contents

| | |
|---------------------------------|--------|
| Specifications | Page 2 |
| Unpacking | Page 3 |
| Connections | Page 3 |
| Video | Page 3 |
| In case of difficulty | Page 3 |
| Warranty | Page 4 |
| Returns | Page 4 |

Rev 0 09-30-1998

Specifications

| | |
|------------------|---|
| Inputs / Outputs | 6 |
| Common | 1 |
| Input level | 1.0Vpp, 75 Ω typical - 10Vpp max. |
| Output level | Same as selected input |
| Connectors | 4 pin mini-DIN female |
| Bandwidth | Greater than 12Mhz |
| Temperature | |
| Operating | 0° ~ 40° C (32° ~ 104° F) |
| Storage | -40° ~ 60° C (-40° ~ 140° F) |
| Humidity | |
| Operating | 10% ~ 90% (non-condensing) |
| Storage | 5% ~ 95% (non-condensing) |
| Size | 6.3" (w) x 5.1" (D) x 1.9" (H) 160 mm (w) x 130 mm (D) x 48 mm (H) |
| Weight | 12 oz. |

Manufactured in the USA by MicroImage Video Systems

Unpacking

The SWP2061 package includes the following items:

SWP2061 Passive Video Switch unit
This operation manual

Please inspect all items carefully and report damaged or missing items to your dealer or MicroImage Video Systems.

Connections

Video

Connect the video sources (i.e. video cameras) to the IN/OUT connectors on the switch unit. Connect the COMMON signal from the switch unit to the video display. Unused inputs may be left unconnected.

The switch will only provide a 75 ohm termination for the selected video signal. Non-selected signals are not terminated.

In case of difficulty

If you are experiencing problems with your MicroImage product, you can contact us in one of the following ways.

| | |
|--------------|--|
| Mail | MicroImage Video Systems a division of World Video Sales Company, Inc. P.O. Box 331 Boyertown, PA 19512 |
| Phone | 610-754-6800 |
| Fax | 610-754-9766 |
| Email | support@mivs.com |
| Web | www.mivs.com |

Warranty

MicroImage Video Systems warrants that each SWP2061 is free from defects due to faulty materials or improper workmanship for a period of one (1) year. MicroImage Video Systems further warrants that any part which proves defective in materials or workmanship within one (1) year, will be replaced or repaired at no cost to the user. Labor to replace defective parts will be done without charge, provided the equipment is returned to MicroImage Video Systems prepaid, insured and properly packaged. Prior return authorization must be obtained from MicroImage Video Systems.

NOTE

This warranty covers the MicroImage SWP2061 Passive Video Switch only.

CONDITIONS

This warranty is void if the warranted part has been altered or subjected to abuse or misuse. Defective parts must be returned to MicroImage Video Systems.

SOLE WARRANTY

This Warranty is in lieu of all other warranties expressed or implied including, without limitation, any implied warranty or any implied warranty of fitness for a particular purpose. MicroImage Video Systems shall have the final right to determination as to the existence and cause of any defect and its appropriate adjustment in accordance with the terms of this warranty. In no event shall MicroImage Video Systems be liable for any consequential or collateral damages.

Returns

All returns MUST have an RMA number. Please call, fax or email for an RMA form. The RMA form will have the proper shipping address for returns.

| | |
|-------|------------------|
| Phone | 610-754-6800 |
| Fax | 610-754-9766 |
| Email | service@mivs.com |